ISO7041 Ultra-Low Power Four-Channel Digital Isolator

1 Features

- Ultra-low power consumption
  - 3.5 μA per channel quiescent current (3.3 V)
  - 15 μA per channel at 100 kbps (3.3 V)
  - 116 μA per channel at 1 Mbps (3.3 V)
- Robust isolation barrier
  - >100-year projected lifetime
  - 3000 V_{RMS} isolation rating
  - ±100 kV/μs typical CMTI
- Wide supply range: 1.71 V to 1.89 V and 2.25 V to 5.5 V
- Wide temperature range:
  - 1.71 V to 1.89 V: –55°C to +105°C
  - 2.25 V to 5.5 V: –55°C to +125°C
- Small 16-QSOP package (16-DBQ)
- Signaling rate: Up to 4 Mbps
- Default output *High* (ISO7041) and *Low* (ISO7041F) options
- Robust electromagnetic compatibility (EMC)
  - System-level ESD, EFT, and surge immunity
  - ±8 kV IEC 61000-4-2 contact discharge protection across isolation barrier
  - Very low emissions
- Safety-related certifications :
  - UL 1577 Component Recognition Program
  - DIN VDE V 0884-11
  - CQC, TUV and CSA
  - IECEx (IEC 60079-0 & IEC 60079-11) and ATEX (EN 60079-0 & EN 60079-11)

2 Applications

- 4-mA to 20-mA loop powered field transmitters
- Factory automation and process automation
- Low-power GPIO, UART and SPI isolation

3 Description

The ISO7041 device is an ultra-low power, multichannel digital isolator that can be used to isolate CMOS or LVCMOS digital I/Os. Each isolation channel has a logic input and output buffer separated by a double capacitive silicon dioxide (SiO_2) insulation barrier. Innovative edge based architecture combined with an ON-OFF keying modulation scheme allows these isolators to consume very-low power while meeting 3000-V_{RMS} isolation rating per UL1577. The per channel dynamic current consumption of the device is under 120 μA/Mbps and the per channel static current consumption is 3.5 μA at 3.3 V, allowing for use of the ISO7041 in both power and thermal constrained system designs.

The device can operate as low as 1.71 V, as high as 5.5 V , and is fully functional with different supply voltages on each side of isolation barrier. The four channel isolator comes in a 16-QSOP package with three forward-direction channels and one reverse-direction channel. The device has default output high and low options. If the input power or signal is lost, default output is *high* for the ISO7041 device without the suffix F and *low* for the ISO7041F device with the F suffix. See the Device Functional Modes section for more information.

Device Information[1]

PART NUMBER	PACKAGE	BODY SIZE (NOM)
ISO7041	QSOP (16)	4.90 mm × 3.90 mm

(1) For all available packages, see the orderable addendum at the end of the data sheet.

Simplified Application Schematic



Data Rate vs Power Consumption at 3.3 V



An IMPORTANT NOTICE at the end of this data sheet addresses availability, warranty, changes, use in safety-critical applications, intellectual property matters and other important disclaimers. PRODUCTION DATA.

Table of Contents

1 Features ... 1
2 Applications ... 1
3 Description ... 1
4 Revision History ... 2
5 Device Comparison Table ... 4
6 Pin Configuration and Functions ... 5
7 Specifications ... 6
7.1 Absolute Maximum Ratings ... 6
7.2 ESD Ratings ... 6
7.3 Recommended Operating Conditions ... 6
7.4 Thermal Information ... 8
7.5 Power Ratings ... 8
7.6 Insulation Specifications ... 9
7.7 Safety-Related Certifications ... 10
7.8 Safety Limiting Values ... 10
7.9 Electrical Characteristics 5V Supply ... 11
7.10 Supply Current Characteristics 5V Supply ... 11
7.11 Electrical Characteristics 3.3V Supply ... 13
7.12 Supply Current Characteristics 3.3V Supply ... 13
7.13 Electrical Characteristics 2.5V Supply ... 15
7.14 Supply Current Characteristics 2.5V Supply ... 15
7.15 Electrical Characteristics 1.8V Supply ... 16
7.16 Supply Current Characteristics 1.8V Supply ... 16
7.17 Switching Characteristics ... 17
7.18 Insulation Characteristics Curves ... 18
7.19 Typical Characteristics ... 18
8 Parameter Measurement Information ... 20
9 Detailed Description ... 21
9.1 Overview ... 21
9.2 Functional Block Diagram ... 21
9.3 Feature Description ... 21
9.4 Device Functional Modes ... 23
10 Application and Implementation ... 25
10.1 Application Information ... 25
10.2 Typical Application ... 27
11 Power Supply Recommendations ... 29
12 Layout ... 30
12.1 Layout Guidelines ... 30
12.2 Layout Example ... 30
13 Device and Documentation Support ... 31
13.1 Documentation Support ... 31
13.2 Receiving Notification of Documentation Updates ... 31
13.3 Community Resource ... 31
13.4 Trademarks ... 31
13.5 Electrostatic Discharge Caution ... 31
13.6 Glossary ... 31
14 Mechanical, Packaging, and Orderable Information ... 31

4 Revision History

NOTE: Page numbers for previous revisions may differ from page numbers in the current version.

Changes from Revision C (January 2020) to Revision D	Page
• Increased supply range to support 1.71 V to 1.89 V	1
• Increased 3.6 V to 5.5 V support temperature range to 125°C and added -55°C to 105°C temperature range for 1.71 V to 1.89 V support	1
• Increased max signaling rate to 4 Mbps	1
• Increased maximum data rate to 4 Mbps	4
• Added 1.8 V support to Recommended Operating Conditions	6
• Changed data rate maximum to 4 Mbps in Recommended Operating Conditions	7
• Added temperature range for 1.71 V to 1.89 V supply range	7
• Added up to 5.5 V support across entire temperature range	7
• Added 1.8 V support in Safety Limiting Values	10
• Added 1.8 V Electrical Characteristics	16
• Added 1.8 V supply current characteristics	16
• Added 1.8 V support to Switching Characteristics	17
• Changed minimum pulse width to 250 ns in Switching Characteristics	17
• Updated all datasheet plots and curves to support 1.8 V	18
• Added 1.8 V support to Functional Table	23
• Added 1.8 V support to the Application Information	25
• Extended power supply range to support 1.71 V to 1.89 V in Design Requirements	28
• Updated speed to 4 Mbps	29
• Added eye diagrams for full voltage range support and 4 Mbps	29

Copyright © 2017–2020, Texas Instruments Incorporated

Changes from Revision B (July 2019) to Revision C **Page**

- Removed (planned) for Safety-related certifications in Features 1
- Added Certificate numbers for all agencies..... 10
- Added *Intrinsic Safety* section 27

Changes from Revision A (December 2018) to Revision B **Page**

- Updated front page channel quiescent current to match data in tables..... 1
- Increased supply range to support up to 5.5 V in Features 1
- Split temperature range to support -40°C for 3.6 V to 5.5 V in Features..... 1
- Added ±8 kV IEC 61000-4-2 contact discharge protection across isolation barrier in Features..... 1
- Increased supply range to 5.5 V in Description..... 1
- Added ±8 kV IEC 61000-4-2 contact discharge protection across isolation barrier..... 6
- Added 5 V support to Recommended Operating Conditions 6
- Added power dissipation maximum numbers to support 5.5 V in Power Ratings..... 8
- Added 5.5 V support in Safety Limiting Values..... 10
- Added 5 V Electrical Characteristics section..... 11
- Added 5 V Supply Current Characteristics section 11
- Updated Device I/O schematics removing (F version) only text in Figure 15 24

Copyright © 2017–2020, Texas Instruments Incorporated

5 Device Comparison Table

Table 1. Device Features

PART NUMBER	CHANNEL DIRECTION	MAXIMUM DATA RATE	DEFAULT OUTPUT	PACKAGE	RATED ISOLATION
ISO7041	3 Forward, 1 Reverse	4 Mbps	High	DBQ-16	3000 V_{RMS} / 4242 V_{PK}
ISO7041 with F suffix	3 Forward, 1 Reverse	4 Mbps	Low	DBQ-16	3000 V_{RMS} / 4242 V_{PK}

Copyright © 2017–2020, Texas Instruments Incorporated

6 Pin Configuration and Functions

ISO7041 DBQ Package
16-Pin QSOP
Top View



Not to scale

Pin Functions

PIN		I/O	DESCRIPTION
NAME	NO.		
EN1	7	I	Refresh enable 1. Refresh is enabled when the EN1 pin is connected to GND1. Disable refresh by connecting the EN1 pin high to V_{CC1}. EN1 and EN2 must be connected to the same logic state to enable or disable refresh.
EN2	10	I	Refresh enable 2. Refresh is enabled when the EN2 pin is connected to GND2. Disable refresh by connecting the EN2 pin high to V_{CC2}. EN1 and EN2 must be connected to the same logic state to enable or disable refresh.
GND1	2	—	Ground connection for V_{CC1}
	8		
GND2	9	—	Ground connection for V_{CC2}
	15		
INA	3	I	Input, channel A
INB	4	I	Input, channel B
INC	5	I	Input, channel C
IND	11	I	Input, channel D
OUTA	14	O	Output, channel A
OUTB	13	O	Output, channel B
OUTC	12	O	Output, channel C
OUTD	6	O	Output, channel D
V_{CC1}	1	—	Power supply, side 1
V_{CC2}	16	—	Power supply, side 2

Copyright © 2017–2020, Texas Instruments Incorporated

7 Specifications

7.1 Absolute Maximum Ratings

over operating free-air temperature range (unless otherwise noted)(1)(2)(3)

		MIN	MAX	UNIT
Supply Voltage	V_{CC1} to GND1	-0.5	6	V
	V_{CC2} to GND2	-0.5	6	
Input/Output Voltage	INx to GNDx	-0.5	V_{CCX} + 0.5	V
	OUTx to GNDx	-0.5	V_{CCX} + 0.5	
	ENx to GNDx	-0.5	V_{CCX} + 0.5	
Output Current	Io	-15	15	mA
Temperature	Operating junction temperature, T_J		150	°C
	Storage temperature, T_{stg}	-65	150	°C

(1) Stresses beyond those listed under Absolute Maximum Ratings may cause permanent damage to the device. These are stress ratings only, which do not imply functional operation of the device at these or any other conditions beyond those indicated under Recommended Operating Conditions. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.
(2) All voltage values except differential I/O bus voltages are with respect to the local ground terminal (GND1 or GND2) and are peak voltage values
(3) Maximum voltage must not exceed 6 V.

7.2 ESD Ratings

			VALUE	UNIT
$V_{(ESD)}$	Electrostatic discharge	Human body model (HBM), per ANSI/ESDA/JEDEC JS-001, all pins(1)	±6000	V
		Charged device model (CDM), per JEDEC specification JESD22-C101, all pins(2)	±1500	
		Contact discharge per IEC 61000-4-2; Isolation barrier withstand test(3)(4)	±8000	

(1) JEDEC document JEP155 states that 500-V HBM allows safe manufacturing with a standard ESD control process.
(2) JEDEC document JEP157 states that 250-V CDM allows safe manufacturing with a standard ESD control process.
(3) IEC ESD strike is applied across the barrier with all pins on each side tied together creating a two-terminal device.
(4) Testing is carried out in air or oil to determine the intrinsic contact discharge capability of the device.

7.3 Recommended Operating Conditions

over operating free-air temperature range (unless otherwise noted)

			MIN	NOM	MAX	UNIT
V_{CC1}(1)	Supply Voltage Side 1		1.71		1.89	V
V_{CC1}(1)	Supply Voltage Side 1		2.25		5.5	V
V_{CC2}(1)	Supply Voltage Side 2		1.71		1.89	V
V_{CC2}(1)	Supply Voltage Side 2		2.25		5.5	V
V_{IH}	High level Input voltage		0.7 x V_{CCI}(2)		V_{CCI}	V
V_{IL}	Low level Input voltage		0		0.3 x V_{CCI}	V
I_{OH}	High level output current	V_{CCO}(2) = 5 V	-4			mA
		V_{CCO} = 3.3 V	-2			mA
		V_{CCO} = 2.5 V	-1			mA
		V_{CCO} = 1.8 V	-1			mA
I_{OL}	Low level output current	V_{CCO} = 5 V			4	mA
		V_{CCO} = 3.3 V			2	mA
		V_{CCO} = 2.5 V			1	mA
		V_{CCO} = 1.8 V			1	mA

(1) V_{CC1} and V_{CC2} can be set independent of one another
(2) V_{CCI} = Input-side V_{CC}; V_{CCO} = Output-side V_{CC}

Copyright © 2017–2020, Texas Instruments Incorporated

Recommended Operating Conditions (continued)

over operating free-air temperature range (unless otherwise noted)

			MIN	NOM	MAX	UNIT
DR	Data Rate		0		4	Mbps
T_A	Ambient temperature	V_{CC1}, V_{CC2} = 1.71 V to 1.89 V	-55		105	°C
		V_{CC1}, V_{CC2} = 2.25 V to 5.5 V	-55		125	°C

Copyright © 2017–2020, Texas Instruments Incorporated

7.4 Thermal Information

THERMAL METRIC(1)		ISO7041 DBQ (SOIC) 16 PINS	UNIT
$R_{\theta JA}$	Junction-to-ambient thermal resistance	87.0	°C/W
$R_{\theta JC(top)}$	Junction-to-case (top) thermal resistance	33.3	°C/W
$R_{\theta JB}$	Junction-to-board thermal resistance	49.1	°C/W
ψ_{JT}	Junction-to-top characterization parameter	8.4	°C/W
ψ_{JB}	Junction-to-board characterization parameter	48.5	°C/W
$R_{\theta JC(bot)}$	Junction-to-case (bottom) thermal resistance	—	°C/W

(1) For more information about traditional and new thermal metrics, see the *Semiconductor and IC Package Thermal Metrics* application report.

7.5 Power Ratings

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
P_D	Maximum power dissipation (both sides)	V_{CC1} = V_{CC2} = 5.5 V, T_J = 150°C, C_L = 15 pF, Input a 1-MHz 50% duty cycle square wave			7.82	mW
P_{D1}	Maximum power dissipation (side-1)				4.46	mW
P_{D2}	Maximum power dissipation (side-2)				3.36	mW

Copyright © 2017–2020, Texas Instruments Incorporated

7.6 Insulation Specifications

PARAMETER		TEST CONDITIONS	SPECIFICATIONS	UNIT
			QSOP-16	
IEC 60664-1				
CLR	External clearance(1)	Side 1 to side 2 distance through air	>3.7	mm
CPG	External creepage(1)	Side 1 to side 2 distance across package surface	>3.7	mm
DTI	Distance through the insulation	Minimum internal gap (internal clearance)	17	µm
CTI	Comparative tracking index	IEC 60112; UL 746A	>600	V
	Material Group		I	
	Overvoltage category	Rated mains voltage ≤ 300 V_{RMS}	I-III	
DIN VDE V 0884-11:2017-01(2)				
V_{IORM}	Maximum repetitive peak isolation voltage	AC voltage (bipolar)	566	V_{PK}
V_{IOWM}	Maximum isolation working voltage	AC voltage (sine wave); time-dependent dielectric breakdown (TDDB) test; See Figure 17	400	V_{RMS}
		DC voltage	566	V_{DC}
V_{IOTM}	Maximum transient isolation voltage	$V_{TEST} = V_{IOTM}$, t = 60 s (qualification); $V_{TEST} = 1.2 \times V_{IOTM}$, t = 1 s (100% production)	4242	V_{PK}
V_{IOSM}	Maximum surge isolation voltage(3)	Test method per IEC 62368-1, 1.2/50 µs waveform, $V_{TEST} = 1.6 \times V_{IOSM} = 6400\ V_{PK}$ (qualification)	4000	V_{PK}
q_{pd}	Apparent charge(4)	Method a: After I/O safety test subgroup 2/3, $V_{ini} = V_{IOTM}$, t_{ini} = 60 s; $V_{pd(m)} = 1.2 \times V_{IORM}$, t_m = 10 s	≤ 5	pC
		Method a: After environmental tests subgroup 1, $V_{ini} = V_{IOTM}$, t_{ini} = 60 s; $V_{pd(m)} = 1.6 \times V_{IORM}$, t_m = 10 s	≤ 5	
		Method b1: At routine test (100% production) and preconditioning (type test), $V_{ini} = V_{IOTM}$, t_{ini} = 1 s; $V_{pd(m)} = 1.875 \times V_{IORM}$, t_m = 1 s	≤ 5	
C_{IO}	Barrier capacitance, input to output(5)	V_{IO} = 0.4 × sin (2 πft), f = 1 MHz	~1.5	pF
R_{IO}	Insulation resistance, input to output(5)	V_{IO} = 500 V, T_A = 25°C	> 10^{12}	Ω
		V_{IO} = 500 V, 100°C ≤ T_A ≤ 150°C	> 10^{11}	
		V_{IO} = 500 V at T_S = 150°C	> 10^{9}	
	Pollution degree		2	
	Climatic category		55/125/21	
UL 1577				
V_{ISO}	Withstand isolation voltage	$V_{TEST} = V_{ISO}$, t = 60 s (qualification); $V_{TEST} = 1.2 \times V_{ISO}$, t = 1 s (100% production)	3000	V_{RMS}

(1) Creepage and clearance requirements should be applied according to the specific equipment isolation standards of an application. Care should be taken to maintain the creepage and clearance distance of a board design to ensure that the mounting pads of the isolator on the printed-circuit board do not reduce this distance. Creepage and clearance on a printed-circuit board become equal in certain cases. Techniques such as inserting grooves, ribs, or both on a printed circuit board are used to help increase these specifications.
(2) This coupler is suitable for *safe electrical insulation* only within the safety ratings. Compliance with the safety ratings shall be ensured by means of suitable protective circuits.
(3) Testing is carried out in air or oil to determine the intrinsic surge immunity of the isolation barrier.
(4) Apparent charge is electrical discharge caused by a partial discharge (pd).
(5) All pins on each side of the barrier tied together creating a two-pin device.

Copyright © 2017–2020, Texas Instruments Incorporated

7.7 Safety-Related Certifications

VDE	CSA	UL	CQC	TUV	CSA/Sira
Certified according to DIN VDE V 0884-11:2017- 01	Certified according to IEC 60950-1 and IEC 62368-1	Certified according to UL 1577 Component Recognition Program	Certified according to GB4943.1-2011	Certified according to EN 61010-1:2010/A1:2019, EN 60950-1:2006/A2:2013 and EN 62368-1:2014	Certified for use in intrinsic safety (IS) to IS applications under ATEX and IECEx.
Maximum transient isolation voltage, 4242 V_{PK}; Maximum repetitive peak isolation voltage, 566 V_{PK}; Maximum surge isolation voltage, 4000 V_{PK}	3000 V_{RMS} insulation per CSA 60950-1-07+A1+A2, IEC 60950-1 2nd Ed.+A1+A2, CSA 62368-1- 14 and IEC 62368-1:2014 370 V_{RMS} (DBQ-16) maximum working voltage (pollution degree 2, material group I)	Single protection, 3000 V_{RMS}	Basic insulation, Altitude ≤ 5000 m, Tropical Climate, 400 V_{RMS} maximum working voltage	EN 61010-1:2010/A1:2019, 300 V_{RMS} basic isolation EN 60950-1:2006/A2:2013 and EN 62368-1:2014, 400 V_{RMS} basic isolation	ATEX: EN 60079-0:2018 and EN 60079-11:2012 IECEx:IEC 60079-0:2017 (7th Ed) and IEC60079-11:2011 (6th Ed) Markings: II 1G Ex ia IIC Ga See the Intrinsic Safety section
Certificate number: 40040142	Master contract number: 220991	File number: E181974	Certificate: CQC18001199097	Client ID number: 77311	IECEx certificate: IECEx CSA 19.0040U ATEX certificate: CSANe 20ATEX2003U

7.8 Safety Limiting Values

Safety limiting(1) intends to minimize potential damage to the isolation barrier upon failure of input or output circuitry.

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
16-QSOP PACKAGE						
I_S	Safety input, output, or supply current	$R_{\theta JA}$ = 87°C/W, V_I = 5.5 V, T_J = 150°C, T_A = 25°C			261	mA
		$R_{\theta JA}$ = 87°C/W, V_I = 3.6 V, T_J = 150°C, T_A = 25°C			399	mA
		$R_{\theta JA}$ = 87°C/W, V_I = 2.75 V, T_J = 150°C, T_A = 25°C			522	
		$R_{\theta JA}$ = 87°C/W, V_I = 1.89 V, T_J = 150°C, T_A = 25°C			760	mA
P_S	Safety input, output, or total power	$R_{\theta JA}$ = 87°C/W, T_J = 150°C, T_A = 25°C			1435	mW
T_S	Maximum safety temperature				150	°C

(1) The maximum safety temperature, T_S, has the same value as the maximum junction temperature, T_J, specified for the device. The I_S and P_S parameters represent the safety current and safety power respectively. The maximum limits of I_S and P_S should not be exceeded. These limits vary with the ambient temperature, T_A.
The junction-to-air thermal resistance, $R_{\theta JA}$, in the table is that of a device installed on a high-K test board for leaded surface-mount packages. Use these equations to calculate the value for each parameter:
$T_J = T_A + R_{\theta JA} \times P$, where P is the power dissipated in the device.
$T_{J(max)} = T_S = T_A + R_{\theta JA} \times P_S$, where $T_{J(max)}$ is the maximum allowed junction temperature.
$P_S = I_S \times V_I$, where V_I is the maximum input voltage.

Copyright © 2017–2020, Texas Instruments Incorporated

7.9 Electrical Characteristics 5V Supply

over operating free-air temperature range (unless otherwise noted)

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
$V_{IT+(IN)}$	Rising input switching threshold				0.7 x V_{CCI} (1)	V
$V_{IT-(IN)}$	Falling input switching threshold		0.3 x V_{CCI}			V
V_{OH}	High-level output voltage	I_{OH} = -4 mA	V_{CCO} - 0.4			V
V_{OL}	Low-level output voltage	I_{OL} = 4 mA			0.4	V
$V_{I(HYS)}$	Input threshold voltage hysteresis		0.1 x V_{CCI}			V
I_{IH}	High-level input current	V_{IH} = V_{CCI} (1) at INx			1	µA
I_{IL}	Low-level input current	V_{IL} = 0 V at INx	-1			µA
CMTI	Common mode transient immunity	V_I = V_{CC} or 0 V, V_{CM} = 1200 V	50	100		kV/us
C_i	Input Capacitance (2)	V_I = V_{CC}/ 2 + 0.4×sin(2πft), f = 1 MHz, V_{CC} = 5 V		2		pF

(1) V_{CCI} = Input-side V_{CC}; V_{CCO} = Output-side V_{CC}
(2) Measured from input pin to same side ground.

7.10 Supply Current Characteristics 5V Supply

over operating free-air temperature range (unless otherwise noted)

PARAMETER	TEST CONDITIONS	SUPPLY CURRENT	MIN	TYP	MAX	UNIT
ISO7041						
Supply current - DC signal	Refresh disable	I_{CC1}		6.2	14.3	µA
		I_{CC2}		10.1	18.5	µA
	Refresh enable V_I = V_{CC1} (ISO7041); V_I = 0 V (ISO7041 with F suffix)	I_{CC1}		8.2	16.7	µA
		I_{CC2}		10.8	18.5	µA
	Refresh enable V_I = 0 V (ISO7041); V_I = V_{CC1} (ISO7041 with F suffix)	I_{CC1}		9.5	19.9	µA
		I_{CC2}		11.3	19.5	µA
Supply current - AC signal	Refresh disable 10 kbps, No Load	I_{CC1}		6.7	19.7	µA
		I_{CC2}		11.8	20.6	µA
	Refresh disable 100 kbps, No Load	I_{CC1}		37.1	57.4	µA
		I_{CC2}		25.8	37.7	µA
	Refresh disable 1 Mbps, No Load	I_{CC1}		340.5	436.1	µA
		I_{CC2}		167.0	211.1	µA
	Refresh enable 10 kbps, No Load	I_{CC1}		10.6	20.8	µA
		I_{CC2}		11.9	20.4	µA
	Refresh enable 100 kbps, No Load	I_{CC1}		37.1	57.4	µA
		I_{CC2}		25.8	37.7	µA
	Refresh enable 1 Mbps, No Load	I_{CC1}		338.3	436.1	µA
		I_{CC2}		166.0	211.1	µA
Total Supply Current Per Channel, Refresh Disabled	DC Signal	$I_{CC1(ch)}$ + $I_{CC2(ch)}$		4.1	7.4	µA
	10 kbps, No Load	$I_{CC1(ch)}$ + $I_{CC2(ch)}$		5.9	10.7	µA
	100 kbps, No Load	$I_{CC1(ch)}$ + $I_{CC2(ch)}$		17.4	23.4	µA
	1 Mbps, No Load	$I_{CC1(ch)}$ + $I_{CC2(ch)}$		137.0	164.5	µA

Copyright © 2017–2020, Texas Instruments Incorporated

Supply Current Characteristics 5V Supply (continued)

over operating free-air temperature range (unless otherwise noted)

PARAMETER	TEST CONDITIONS	SUPPLY CURRENT	MIN	TYP	MAX	UNIT
Total Supply Current Per Channel, Refresh Enabled	$V_I = V_{CC1}$ (ISO7041); $V_I = 0$ V (ISO7041 with F suffix)	$I_{CC1(ch)} + I_{CC2(ch)}$		4.8	8.5	µA
	$V_I = 0$ V (ISO7041); $V_I = V_{CC1}$ (ISO7041 with F suffix)	$I_{CC1(ch)} + I_{CC2(ch)}$		5.3	9.6	µA
	10 kbps, No Load	$I_{CC1(ch)} + I_{CC2(ch)}$		5.7	10.4	µA
	100 kbps, No Load	$I_{CC1(ch)} + I_{CC2(ch)}$		16.4	22.3	µA
	1 Mbps, No Load	$I_{CC1(ch)} + I_{CC2(ch)}$		125.9	154.0	µA

Copyright © 2017–2020, Texas Instruments Incorporated

7.11 Electrical Characteristics 3.3V Supply

over operating free-air temperature range (unless otherwise noted)

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
$V_{IT+(IN)}$	Rising input switching threshold				0.7 x V_{CCI} (1)	V
$V_{IT-(IN)}$	Falling input switching threshold		0.3 x V_{CCI}			V
V_{OH}	High-level output voltage	I_{OH} = -2mA	V_{CCO} - 0.3	V_{CCO} - 0.2		V
V_{OL}	Low-level output voltage	I_{OL} = 2mA		0.2	0.3	V
$V_{I(HYS)}$	Input threshold voltage hysteresis		0.1 x V_{CCI}			V
I_{IH}	High-level input current	V_{IH} = V_{CCI} (1) at INx			1	µA
I_{IL}	Low-level input current	V_{IL} = 0 V at INx	-1			µA
CMTI	Common mode transient immunity	V_I = V_{CC} or 0 V, V_{CM} = 1200 V	50	100		kV/us
C_i	Input Capacitance (2)	V_I = V_{CC}/ 2 + 0.4×sin(2πft), f = 1 MHz, V_{CC} = 3.6 V		2		pF

(1) V_{CCI} = Input-side V_{CC}; V_{CCO} = Output-side V_{CC}
(2) Measured from input pin to same side ground.

7.12 Supply Current Characteristics 3.3V Supply

over operating free-air temperature range (unless otherwise noted)

PARAMETER	TEST CONDITIONS	SUPPLY CURRENT	MIN	TYP	MAX	UNIT
ISO7041						
Supply current - DC signal	Refresh disable	I_{CC1}		5.1	8.8	µA
		I_{CC2}		8.9	14.0	µA
	Refresh enable V_I = V_{CC1} (ISO7041); V_I = 0 V (ISO7041 with F suffix)	I_{CC1}		6.8	12.2	µA
		I_{CC2}		9.6	14.0	µA
	Refresh enable V_I = 0 V (ISO7041); V_I = V_{CC1} (ISO7041 with F suffix)	I_{CC1}		8.1	14.8	µA
		I_{CC2}		10.0	15.6	µA
Supply current - AC signal	Refresh disable 10 kbps, No Load	I_{CC1}		7.9	13.7	µA
		I_{CC2}		10.4	15.9	µA
	Refresh disable 100 kbps, No Load	I_{CC1}		35.9	48.3	µA
		I_{CC2}		22.7	31.4	µA
	Refresh disable 1 Mbps, No Load	I_{CC1}		316.4	395.7	µA
		I_{CC2}		147.2	188.2	µA
	Refresh enable 10 kbps, No Load	I_{CC1}		9.8	16.4	µA
		I_{CC2}		10.5	16.2	µA
	Refresh enable 100 kbps, No Load	I_{CC1}		35.9	48.3	µA
		I_{CC2}		22.7	31.4	µA
	Refresh enable 1 Mbps, No Load	I_{CC1}		315.3	395.7	µA
		I_{CC2}		146.2	188.2	µA
Total Supply Current Per Channel, Refresh Disabled	DC Signal	$I_{CC1(ch)}$ + $I_{CC2(ch)}$		3.5	5.7	µA
	10 kbps, No Load	$I_{CC1(ch)}$ + $I_{CC2(ch)}$		5.2	8.2	µA
	100 kbps, No Load	$I_{CC1(ch)}$ + $I_{CC2(ch)}$		14.8	19.2	µA
	1 Mbps, No Load	$I_{CC1(ch)}$ + $I_{CC2(ch)}$		115.7	138.7	µA

Copyright © 2017–2020, Texas Instruments Incorporated

Supply Current Characteristics 3.3V Supply (continued)

over operating free-air temperature range (unless otherwise noted)

PARAMETER	TEST CONDITIONS	SUPPLY CURRENT	MIN	TYP	MAX	UNIT
Total Supply Current Per Channel, Refresh Enabled	$V_I = V_{CC1}$ (ISO7041); $V_I = 0$ V (ISO7041 with F suffix)	$I_{CC1(ch)} + I_{CC2(ch)}$		4.2	6.8	µA
	$V_I = 0$ V (ISO7041); $V_I = V_{CC1}$ (ISO7041 with F suffix)	$I_{CC1(ch)} + I_{CC2(ch)}$		4.6	7.7	µA
	10 kbps, No Load	$I_{CC1(ch)} + I_{CC2(ch)}$		5.2	8.2	µA
	100 kbps, No Load	$I_{CC1(ch)} + I_{CC2(ch)}$		14.8	19.2	µA
	1 Mbps, No Load	$I_{CC1(ch)} + I_{CC2(ch)}$		115.7	138.7	µA

Copyright © 2017–2020, Texas Instruments Incorporated

7.13 Electrical Characteristics 2.5V Supply

over operating free-air temperature range (unless otherwise noted)

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
$V_{IT+(IN)}$	Rising input switching threshold				0.7 x V_{CCI} (1)	V
$V_{IT-(IN)}$	Falling input switching threshold		0.3 x V_{CCI}			V
V_{OH}	High-level output voltage	I_{OH} = -1mA	V_{CCO} - 0.2			V
V_{OL}	Low-level output voltage	I_{OL} = 1mA			0.2	V
$V_{I(HYS)}$	Input threshold voltage hysteresis		0.1 x V_{CCI}			V
I_{IH}	High-level input current	V_{IH} = V_{CCI} (1) at INx			1	µA
I_{IL}	Low-level input current	V_{IL} = 0 V at INx	-1			µA
CMTI	Common mode transient immunity	V_I = V_{CC} or 0 V, V_{CM} = 1200 V	50	100		kV/us

(1) V_{CCI} = Input-side V_{CC}; V_{CCO} = Output-side V_{CC}

7.14 Supply Current Characteristics 2.5V Supply

over operating free-air temperature range (unless otherwise noted)

PARAMETER	TEST CONDITIONS	SUPPLY CURRENT	MIN	TYP	MAX	UNIT
ISO7041						
Supply current - DC signal	Refresh disable	I_{CC1}		4.7	8.2	µA
		I_{CC2}		8.6	13.0	µA
	Refresh enable V_I = V_{CC1} (ISO7041); V_I = 0 V (ISO7041 with F suffix)	I_{CC1}		6.4	10.9	µA
		I_{CC2}		9.2	13.0	µA
	Refresh enable V_I = 0 V (ISO7041); V_I = V_{CC1} (ISO7041 with F suffix)	I_{CC1}		7.6	13.2	µA
		I_{CC2}		9.6	14.6	µA
Supply current - AC signal	Refresh disable 10 kbps, No Load	I_{CC1}		8.2	12.2	µA
		I_{CC2}		10.0	14.8	µA
	Refresh disable 100 kbps, No Load	I_{CC1}		34.7	44.5	µA
		I_{CC2}		21.3	29.0	µA
	Refresh disable 1 Mbps, No Load	I_{CC1}		301.5	367.4	µA
		I_{CC2}		137.0	173.3	µA
	Refresh enable 10 kbps, No Load	I_{CC1}		9.9	14.6	µA
		I_{CC2}		10.0	15.9	µA
	Refresh enable 100 kbps, No Load	I_{CC1}		34.7	44.5	µA
		I_{CC2}		21.3	29.0	µA
	Refresh enable 1 Mbps, No Load	I_{CC1}		304.8	367.4	µA
		I_{CC2}		136.0	173.3	µA
Total Supply Current Per Channel, Refresh Disabled	DC Signal	$I_{CC1(ch)}$ + $I_{CC2(ch)}$		3.3	5.3	µA
	10 kbps, No Load	$I_{CC1(ch)}$ + $I_{CC2(ch)}$		5.0	7.5	µA
	100 kbps, No Load	$I_{CC1(ch)}$ + $I_{CC2(ch)}$		14.0	17.6	µA
	1 Mbps, No Load	$I_{CC1(ch)}$ + $I_{CC2(ch)}$		110.0	127.1	µA
Total Supply Current Per Channel, Refresh Enabled	V_I = V_{CC1} (ISO7041); V_I = 0 V (ISO7041 with F suffix)	$I_{CC1(ch)}$ + $I_{CC2(ch)}$		4.0	6.2	µA
	V_I = 0 V (ISO7041); V_I = V_{CC1} (ISO7041 with F suffix)	$I_{CC1(ch)}$ + $I_{CC2(ch)}$		4.4	7.0	µA
	10 kbps, No Load	$I_{CC1(ch)}$ + $I_{CC2(ch)}$		5.0	7.5	µA
	100 kbps, No Load	$I_{CC1(ch)}$ + $I_{CC2(ch)}$		14.0	17.6	µA
	1 Mbps, No Load	$I_{CC1(ch)}$ + $I_{CC2(ch)}$		110	127.1	µA

Copyright © 2017–2020, Texas Instruments Incorporated

7.15 Electrical Characteristics 1.8V Supply

over operating free-air temperature range (unless otherwise noted)

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
$V_{IT+(IN)}$	Rising input switching threshold				0.7 x V_{CCI} (1)	V
$V_{IT-(IN)}$	Falling input switching threshold		0.3 x V_{CCI}			V
V_{OH}	High-level output voltage	I_{OH} = -1mA	V_{CCO} - 0.2			V
V_{OL}	Low-level output voltage	I_{OL} = 1mA			0.2	V
$V_{I(HYS)}$	Input threshold voltage hysteresis		0.1 x V_{CCI}			V
I_{IH}	High-level input current	V_{IH} = V_{CCI} (1) at INx			1	µA
I_{IL}	Low-level input current	V_{IL} = 0 V at INx	-1			µA
CMTI	Common mode transient immunity	V_I = V_{CC} or 0 V, V_{CM} = 1200 V	50	100		kV/us

(1) V_{CCI} = Input-side V_{CC}; V_{CCO} = Output-side V_{CC}

7.16 Supply Current Characteristics 1.8V Supply

over operating free-air temperature range (unless otherwise noted)

PARAMETER	TEST CONDITIONS	SUPPLY CURRENT	MIN	TYP	MAX	UNIT
ISO7041						
Supply current - DC signal	Refresh disable	I_{CC1}		3.7	7.5	µA
		I_{CC2}		7.9	13.3	µA
	Refresh enable V_I = V_{CCI} (1) (ISO7041); V_I = 0 V (ISO7041 with F suffix)	I_{CC1}		5.1	9.6	µA
		I_{CC2}		8.6	14.1	µA
	Refresh enable V_I = 0 V (ISO7041); V_I = V_{CCI} (ISO7041 with F suffix)	I_{CC1}		6.3	11.5	µA
		I_{CC2}		9.0	14.7	µA
Supply current - AC signal	Refresh disable 10 kbps, No Load	I_{CC1}		9.3	10.9	µA
		I_{CC2}		9.3	15.2	µA
	Refresh disable 100 kbps, No Load	I_{CC1}		31.7	40.6	µA
		I_{CC2}		21.2	31.0	µA
	Refresh disable 1 Mbps, No Load	I_{CC1}		255.2	338.4	µA
		I_{CC2}		140.8	190.8	µA
	Refresh enable 10 kbps, No Load	I_{CC1}		7	12.9	µA
		I_{CC2}		9.5	15	µA
	Refresh enable 100 kbps, No Load	I_{CC1}		31.6	40.6	µA
		I_{CC2}		21.2	31.0	µA
	Refresh enable 1 Mbps, No Load	I_{CC1}		256.3	338.4	µA
		I_{CC2}		140.8	190.8	µA
Total Supply Current Per Channel, Refresh Disabled	DC Signal	$I_{CC1(ch)}$ + $I_{CC2(ch)}$		2.8	5.2	µA
	10 kbps, No Load	$I_{CC1(ch)}$ + $I_{CC2(ch)}$		3.8	6.4	µA
	100 kbps, No Load	$I_{CC1(ch)}$ + $I_{CC2(ch)}$		12.5	17.1	µA
	1 Mbps, No Load	$I_{CC1(ch)}$ + $I_{CC2(ch)}$		99	124.8	µA
Total Supply Current Per Channel, Refresh Enabled	V_I = V_{CCI} (ISO7041); V_I = 0 V (ISO7041 with F suffix)	$I_{CC1(ch)}$ + $I_{CC2(ch)}$		3.4	8	µA
	V_I = 0 V (ISO7041); V_I = V_{CCI} (ISO7041 with F suffix)	$I_{CC1(ch)}$ + $I_{CC2(ch)}$		3.8	8.9	µA
	10 kbps, No Load	$I_{CC1(ch)}$ + $I_{CC2(ch)}$		4.1	6.8	µA
	100 kbps, No Load	$I_{CC1(ch)}$ + $I_{CC2(ch)}$		12.5	17.1	µA
	1 Mbps, No Load	$I_{CC1(ch)}$ + $I_{CC2(ch)}$		99.3	124.8	µA

(1) V_{CCI} = Input-side V_{CC}

Copyright © 2017–2020, Texas Instruments Incorporated

7.17 Switching Characteristics

V_{CC1}, V_{CC2} = 1.71 V to 1.89 V or 2.25 V to 5.5 V (over recommended operating conditions unless otherwise noted)

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
t_{PLH}, t_{PHL}	Propagation delay time	See Figure 11		140	175	ns
				140	165	ns
$t_{P(dft)}$	Propagation delay drift			15		ps/℃
t_{UI}	Minimum pulse width	See Figure 11	250			ns
PWD	Pulse width distortion				10	ns
$t_{sk(o)}$	Channel to channel output skew time	Same-direction channels			10	ns
		Opposite-direction channels			10	ns
$t_{sk(p-p)}$	Part to part skew time				70	ns
t_r	Output signal rise time	V_{CC1}, V_{CC2} = 1.71 V to 1.89 V. See Figure 11			8	ns
		V_{CC1}, V_{CC2} = 2.25 V to 5.5 V. See Figure 11			5	ns
t_f	Output signal fall time	V_{CC1}, V_{CC2} = 1.71 V to 1.89 V. See Figure 11			8	ns
		V_{CC1}, V_{CC2} = 2.25 V to 5.5 V. See Figure 11			5	ns
t_{DO}	Default output delay time from input power loss	Refresh enabled, See Figure 12		400	750	us
t_{PU}	Time from UVLO to valid output data		1		5	ms
F_R	Refresh rate		5	10		kbps

Copyright © 2017–2020, Texas Instruments Incorporated

7.18 Insulation Characteristics Curves



Figure 1. Thermal Derating Curve for Limiting Current per VDE



Figure 2. Thermal Derating Curve for Limiting Power per VDE

7.19 Typical Characteristics



T_A = 25°C C_L = 0 pF

Figure 3. ISO7041 Supply Current vs Data Rate at 1.8 V (With No Load)



T_A = 25°C C_L = 15 pF

Figure 4. ISO7041 Supply Current vs Data Rate at 1.8 V (With 15-pF Load)



T_A = 25°C C_L = 0 pF

Figure 5. ISO7041 Supply Current vs Data Rate at 2.5 V (With No Load)



T_A = 25°C C_L = 15 pF

Figure 6. ISO7041 Supply Current vs Data Rate at 2.5 V (With 15-pF Load)

Copyright © 2017–2020, Texas Instruments Incorporated

Typical Characteristics (continued)



T_A = 25°C C_L = 0 pF

Figure 7. ISO7041 Supply Current vs Data Rate at 3.3 V (With No Load)



T_A = 25°C C_L = 15 pF

Figure 8. ISO7041 Supply Current vs Data Rate at 3.3 V (With 15-pF Load)



T_A = 25°C C_L = 0 pF

Figure 9. ISO7041 Supply Current vs Data Rate at 5 V (With No Load)



T_A = 25°C C_L = 15 pF

Figure 10. ISO7041 Supply Current vs Data Rate at 5 V (With 15-pF Load)

Copyright © 2017–2020, Texas Instruments Incorporated

8 Parameter Measurement Information



A. The input pulse is supplied by a generator having the following characteristics: PRR ≤ 50 kHz, 50% duty cycle, t_r ≤ 3 ns, t_f ≤ 3ns, Z_O = 50 Ω. At the input, 50 Ω resistor is required to terminate Input Generator signal. It is not needed in actual application.

B. C_L = 15 pF and includes instrumentation and fixture capacitance within ±20%.

Figure 11. Switching Characteristics Test Circuit and Voltage Waveforms



A. C_L = 15 pF and includes instrumentation and fixture capacitance within ±20%.

B. Power Supply Ramp Rate = 10 mV/ns

Figure 12. Default Output Delay Time Test Circuit and Voltage Waveforms



A. C_L = 15 pF and includes instrumentation and fixture capacitance within ±20%.

Figure 13. Common-Mode Transient Immunity Test Circuit

Copyright © 2017–2020, Texas Instruments Incorporated

9 Detailed Description

9.1 Overview

The ISO7041 device uses edge encoding of data with an ON-OFF keying (OOK) modulation scheme to transmit the digital data across a silicon dioxide isolation barrier. The transmitter uses a high frequency carrier signal to pass data across the barrier representing a signal edge transition. Using this method achieves very low power consumption and high immunity. The receiver demodulates the carrier signal after advanced signal conditioning and produces the output through a buffer stage. For low data rates, a refresh logic option is available to make sure the output state matches the input state. The ENx pins of side A and side B must be tied low to enable refresh or high to disable refresh. Advanced circuit techniques are used to maximize the CMTI performance and minimize the radiated emissions due to the high frequency carrier and IO buffer switching. The conceptual block diagram of a digital capacitive isolator, Figure 14, shows a functional block diagram of a typical channel.

9.2 Functional Block Diagram



Figure 14. Conceptual Block Diagram of a Digital Capacitive Isolator

9.3 Feature Description

9.3.1 Refresh Enable

The ISO7041 uses an edge based encoding scheme to transfer an input signal change across the isolation barrier versus sending across the DC state. Enabling the refresh feature consistently validates that the DC output state of each isolator channel matches the DC input state. An internal watchdog timer monitors for activity on the individual inputs and transmits the logic state when there is no input signal transition for more than 100 µs. This ensures that the input and output state of the isolator always match. Tie both EN1 and EN2 to their respective grounds to enable refresh.

Disable refresh by tying both EN1 and EN2 to their respective VCC power supplies. Disabling refresh will further decrease the power consumption of the device but the DC state is not guaranteed at startup. System level solutions can be implemented to ensure the isolator channel output matches the input at startup. For example, at start up, an immediate full transition of the input signals from high to low and low to high on the individual isolator lines would allow the states of the outputs to properly track the inputs.

Copyright © 2017–2020, Texas Instruments Incorporated

Feature Description (continued)

9.3.2 Electromagnetic Compatibility (EMC) Considerations

Many applications in harsh industrial environment are sensitive to disturbances such as electrostatic discharge (ESD), electrical fast transient (EFT), surge and electromagnetic emissions. These electromagnetic disturbances are regulated by international standards such as IEC 61000-4-x and CISPR 22. Although system-level performance and reliability depends, to a large extent, on the application board design and layout, the ISO70xx family of devices incorporates many chip-level design improvements for overall system robustness. Some of these improvements include:

- Robust ESD protection cells for input and output signal pins and inter-chip bond pads.
- Low-resistance connectivity of ESD cells to supply and ground pins.
- Enhanced performance of high voltage isolation capacitor for better tolerance of ESD, EFT and surge events.
- Bigger on-chip decoupling capacitors to bypass undesirable high energy signals through a low impedance path.
- PMOS and NMOS devices isolated from each other by using guard rings to avoid triggering of parasitic SCRs.
- Reduced common mode currents across the isolation barrier by ensuring purely differential internal operation.

The device has no issue being able to meet either CISPR 22 Class A and CISPR22 Class B standards in an unshielded environment.

Copyright © 2017–2020, Texas Instruments Incorporated

9.4 Device Functional Modes

shows the functional modes for the device.

Table 2. Function Table(1)

V_{CCI}	V_{CCO}	INPUT (INx)(2)	REFRESH ENABLE (ENx)	OUTPUT (OUTx)	COMMENTS
PU	PU	H	L	H	Normal Operation: A channel output assumes the logic state of its input.
		L	L	L	
		X	H	Undetermined	The device needs an input signal transition to validate the output tracks the input state. Without a signal edge transition, the output will be in an undetermined state.
PD	PU	X	L	Default	When V_{CCI} is unpowered, a channel output assumes the logic state based on the selected default option. Default is *High* for the device without the F suffix and *Low* for device with the F suffix. When V_{CCI} transitions from unpowered to powered-up, a channel output assumes the logic state of the input. When V_{CCI} transitions from powered-up to unpowered, channel output assumes the selected default state.
			H	Undetermined	When V_{CCI} is unpowered, a channel output assumes the logic state based on the previous state of the output before V_{CCI} powered down.
X	PD	X	L	Undetermined	When V_{CCO} is unpowered, a channel output is undetermined(3). When V_{CCO} transitions from unpowered to powered-up, a channel output assumes the logic state of the input.
			H	Undetermined	When V_{CCO} is unpowered, a channel output is undetermined(3). When V_{CCO} transitions from unpowered to powered-up, a channel output assumes the selected default option.
X	X	X	Open	Undetermined	When ENx is unconnected or open, the device output will be in an undetermined and unknown state. ENx must be connected high or low for the device to behave correctly.

(1) V_{CCI} = Input-side V_{CC}; V_{CCO} = Output-side V_{CC}; PU = Powered up ($V_{CC} \geq 1.54$ V); PD = Powered down ($V_{CC} \leq 1.54$); X = Irrelevant; H = High level; L = Low level ; Z = High Impedance
(2) A strongly driven input signal can weakly power the floating V_{CC} through an internal protection diode and cause undetermined output.
(3) The outputs are in undetermined state when 1.54 V < V_{CCI}, V_{CCO} < 1.54 V.

Copyright © 2017–2020, Texas Instruments Incorporated

9.4.1 Device I/O Schematics



Figure 15. Device I/O Schematics

Copyright © 2017–2020, Texas Instruments Incorporated

10 Application and Implementation

NOTE

Information in the following applications sections is not part of the TI component specification, and TI does not warrant its accuracy or completeness. TI's customers are responsible for determining suitability of components for their purposes. Customers should validate and test their design implementation to confirm system functionality.

10.1 Application Information

The ISO7041 device is an ultra-low power digital isolator. The device uses single-ended CMOS-logic switching technology. The voltage range is from 1.71 V to 1.89 V and 2.25 V to 5.5 V for both supplies, V_{CC1} and V_{CC2}, and can be set irrespective of one another. When designing with digital isolators, keep in mind that because of the single-ended design structure, digital isolators do not conform to any specific interface standard and are only intended for isolating single-ended CMOS or TTL digital signal lines. The isolator is typically placed between the data controller (that is, μC or UART), and a data converter or a line transceiver, regardless of the interface type or standard. See *Isolated power and data interface for low-power applications reference design* TI Design for detailed information on designing the ISO70xx in low-power applications.

10.1.1 *Insulation Lifetime*

Insulation lifetime projection data is collected by using industry-standard Time Dependent Dielectric Breakdown (TDDB) test method. In this test, all pins on each side of the barrier are tied together creating a two-terminal device and high voltage applied between the two sides; see Figure 16 for TDDB test setup. The insulation breakdown data is collected at various high voltages switching at 60 Hz over temperature. For reinforced insulation, VDE standard requires the use of TDDB projection line with failure rate of less than 1 part per million (ppm) and a minimum insulation lifetime of 20 years. VDE standard also requires additional safety margin of 20% for working voltage and 87.5% for insulation lifetime which translates into minimum required life time of 37.5 years.

Figure 17 shows the intrinsic capability of the isolation barrier to withstand high voltage stress over its lifetime. Based on the TDDB data, the intrinsic capability of these devices is 400 VRMS with a lifetime of >100 years. Other factors, such as package size, pollution degree, material group, and so forth can further limit the working voltage of the component. The working voltage of the DBQ-16 package specified up to 400 VRMS. At the lower working voltages, the corresponding insulation barrier life time is much longer.



Figure 16. Test Setup for Insulation Lifetime Measurement

Application Information (continued)



Figure 17. Insulation Lifetime Projection Data

Copyright © 2017–2020, Texas Instruments Incorporated

Application Information (continued)

10.1.2 *Intrinsic Safety*

The ISO7041 supports Intrinsically Safe (IS) to IS applications and carry IECEx and ATEX certifications. These devices do not currently support IS to non-IS galvanic isolation applications due to the minimum insulation thickness requirements of IEC 60079-11.

10.1.2.1 Schedule of Limitations

These components are certified to comply with IEC 60079-0, Edition 7, IEC 60079-11, Edition 6, EN 60079-0:2018 and EN 60070-11:2012. When one of these components is used in an equipment, the component is to be soldered on a PCB inside a suitable enclosure and re-evaluated as an equipment. The operating temperature range of these components is -55°C to +85°C. The creepage and clearance distances across the isolating component have been evaluated, but the distance to other circuitry remain the responsibility of the user of the final equipment.

This assembly is an isolating component between separate intrinsically safe circuits. The assembly must be connected to suitably certified intrinsically safe circuits considering the entity parameters and temperature ratings in the two different application scenarios shown in Table 3.

Table 3. Entity Parameters and Temperature Ratings

APPLICATION	ENTITY PARAMETERS SIDE 1	ENTITY PARAMETERS SIDE 2	AMBIENT TEMPERATURE RANGE	MAXIMUM COMPONENT TEMPERATURE
IS to IS: Case 1	Ui = 50 V	Ui = 50 V	-55°C to +70°C	194.3°C
	Ii = 300 mA	Ii = 300 mA		
	Pi = 1.3 W	Pi = 1.3 W		
	Li = 0 H	Li = 0 H		
	Ci = 4 pF	Ci = 4 pF		
IS to IS: Case 2	Ui = 50 V	Ui = 50 V	-55°C to +85°C	183.1°C
	Ii = 300 mA	Ii = 300 mA		
	Pi = 1.1 W	Pi = 1.1 W		
	Li = 0 H	Li = 0 H		
	Ci = 4 pF	Ci = 4 pF		

10.2 Typical Application

Figure 18 shows the isolated serial peripheral interface (SPI).



Figure 18. Isolated SPI for a Temperature Field Transmitter

Typical Application (continued)

10.2.1 Design Requirements

To design with these devices, use the parameters listed in Table 4.

Table 4. Design Parameters

PARAMETER	VALUE
Supply voltage, V_{CC1} and V_{CC2}	1.71 V to 1.89 V or 2.25 V to 5.5 V
Decoupling capacitor between V_{CC1} and GND1	0.1 µF
Decoupling capacitor from V_{CC2} and GND2	0.1 µF

10.2.2 Detailed Design Procedure

Unlike optocouplers, which require external components to improve performance, provide bias, or limit current, the device only require two external bypass capacitors to operate.



Figure 19. Typical ISO7041 Circuit Hook-up

Copyright © 2017–2020, Texas Instruments Incorporated

10.2.3 Application Curves

The following typical eye diagrams of the device indicates wide open eye at the maximum data rate of 4 Mbps.

Figure 20. Eye Diagram at 4 Mbps PRBS 2^{16} – 1, 1.8 V and 25°C



Figure 21. Eye Diagram at 4 Mbps PRBS 2^{16} – 1, 2.5 V and 25°C



Figure 22. Eye Diagram at 4 Mbps PRBS 2^{16} – 1, 3.3 V and 25°C



Figure 23. Eye Diagram at 4 Mbps PRBS 2^{16} – 1, 5 V and 25°C

11 Power Supply Recommendations

Put a 0.1-µF bypass capacitor at the input and output supply pins (V_{CC1} and V_{CC2}) to make sure that operation is reliable at data rates and supply voltage. Put the capacitors as near to the supply pins as possible. If only one primary-side power supply is available in an application, use a transformer driver to help generate the isolated power for the secondary-side. Texas Instruments recommends the SN6501 device or SN6505A device. Refer to the *SN6501 Transformer Driver for Isolated Power Supplies* data sheet or *SN6505 Low-Noise 1-A Transformer Drivers for Isolated Power Supplies* data sheet for detailed power supply design and transformer selection recommendations.

Copyright © 2017–2020, Texas Instruments Incorporated

12 Layout

12.1 Layout Guidelines

A minimum of four layers is required to accomplish a low EMI PCB design (see Figure 24). Layer stacking should be in the following order (top-to-bottom): high-speed signal layer, ground plane, power plane and low-frequency signal layer.

- Routing the high-speed traces on the top layer avoids the use of vias (and the introduction of their inductances) and allows for clean interconnects between the isolator and the transmitter and receiver circuits of the data link.
- Placing a solid ground plane next to the high-speed signal layer establishes controlled impedance for transmission line interconnects and provides an excellent low-inductance path for the return current flow.
- Placing the power plane next to the ground plane creates additional high-frequency bypass capacitance of approximately 100 pF/in^2.
- Routing the slower speed control signals on the bottom layer allows for greater flexibility as these signal links usually have margin to tolerate discontinuities such as vias.

If an additional supply voltage plane or signal layer is needed, add a second power or ground plane system to the stack to keep it symmetrical. This makes the stack mechanically stable and prevents it from warping. Also the power and ground plane of each power system can be placed closer together, thus increasing the high-frequency bypass capacitance significantly.

Refer to the *Digital Isolator Design Guide* for detailed layout recommendations,.

12.1.1 PCB Material

For digital circuit boards operating at less than 150 Mbps, (or rise and fall times greater than 1 ns), and trace lengths of up to 10 inches, use standard FR-4 UL94V-0 printed circuit board. This PCB is preferred over cheaper alternatives because of lower dielectric losses at high frequencies, less moisture absorption, greater strength and stiffness, and the self-extinguishing flammability-characteristics.

12.2 Layout Example



Figure 24. Recommended Layer Stack

Copyright © 2017–2020, Texas Instruments Incorporated

13 Device and Documentation Support

13.1 Documentation Support

13.1.1 Related Documentation

For related documentation see the following:

- Texas Instruments, *Digital Isolator Design Guide*
- Texas Instruments, *Isolation Glossary*
- Texas Instruments, *ADS1220 4-Channel, 2-kSPS, Low-Power, 24-Bit ADC with Integrated PGA and Reference* data sheet
- Texas Instruments, *ADS122U04 24-Bit, 4-Channel, 2-kSPS, Delta-Sigma ADC With UART Interface* data sheet
- Texas Instruments, *ADS124S0x Low-Power, Low-Noise, Highly Integrated, 6- and 12-Channel, 4-kSPS, 24-Bit, Delta-Sigma ADC with PGA and Voltage Reference* data sheet
- Texas Instruments, *Uniquely Efficient Isolated DC/DC Converter for Ultra-Low Power and Low-Power Applications* TI Design
- Texas Instruments, *SN6501 Transformer Driver for Isolated Power Supplies* data sheet
- Texas Instruments, *SN6505A Low-Noise 1-A Transformer Drivers for Isolated Power Supplies* data sheet
- Texas Instruments, *Isolated power and data interface for low-power applications reference design* TI Design

13.2 Receiving Notification of Documentation Updates

To receive notification of documentation updates, navigate to the device product folder on ti.com. In the upper right corner, click on *Alert me* to register and receive a weekly digest of any product information that has changed. For change details, review the revision history included in any revised document.

13.3 Community Resource

TI E2E™ support forums are an engineer's go-to source for fast, verified answers and design help — straight from the experts. Search existing answers or ask your own question to get the quick design help you need.

Linked content is provided "AS IS" by the respective contributors. They do not constitute TI specifications and do not necessarily reflect TI's views; see TI's Terms of Use.

13.4 Trademarks

E2E is a trademark of Texas Instruments.

13.5 Electrostatic Discharge Caution

This integrated circuit can be damaged by ESD. Texas Instruments recommends that all integrated circuits be handled with appropriate precautions. Failure to observe proper handling and installation procedures can cause damage.

ESD damage can range from subtle performance degradation to complete device failure. Precision integrated circuits may be more susceptible to damage because very small parametric changes could cause the device not to meet its published specifications.

13.6 Glossary

SLYZ022 — *TI Glossary*.

This glossary lists and explains terms, acronyms, and definitions.

14 Mechanical, Packaging, and Orderable Information

The following pages include mechanical packaging and orderable information. This information is the most current data available for the designated devices. This data is subject to change without notice and revision of this document. For browser-based versions of this data sheet, refer to the left-hand navigation.

Copyright © 2017–2020, Texas Instruments Incorporated

PACKAGING INFORMATION

Orderable part number	Status (1)	Material type (2)	Package | Pins	Package qty | Carrier	RoHS (3)	Lead finish/ Ball material (4)	MSL rating/ Peak reflow (5)	Op temp (°C)	Part marking (6)
ISO7041DBQ	Active	Production	SSOP (DBQ) | 16	75 | TUBE	Yes	NIPDAU	Level-2-260C-1 YEAR	-55 to 125	7041
ISO7041DBQR	Active	Production	SSOP (DBQ) | 16	2500 | LARGE T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-55 to 125	7041
ISO7041FDBQ	Active	Production	SSOP (DBQ) | 16	75 | TUBE	Yes	NIPDAU	Level-2-260C-1 YEAR	-55 to 125	7041F
ISO7041FDBQR	Active	Production	SSOP (DBQ) | 16	2500 | LARGE T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-55 to 125	7041F

(1) **Status:** For more details on status, see our product life cycle.

(2) **Material type:** When designated, preproduction parts are prototypes/experimental devices, and are not yet approved or released for full production. Testing and final process, including without limitation quality assurance, reliability performance testing, and/or process qualification, may not yet be complete, and this item is subject to further changes or possible discontinuation. If available for ordering, purchases will be subject to an additional waiver at checkout, and are intended for early internal evaluation purposes only. These items are sold without warranties of any kind.

(3) **RoHS values:** Yes, No, RoHS Exempt. See the TI RoHS Statement for additional information and value definition.

(4) **Lead finish/Ball material:** Parts may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead finish/Ball material values may wrap to two lines if the finish value exceeds the maximum column width.

(5) **MSL rating/Peak reflow:** The moisture sensitivity level ratings and peak solder (reflow) temperatures. In the event that a part has multiple moisture sensitivity ratings, only the lowest level per JEDEC standards is shown. Refer to the shipping label for the actual reflow temperature that will be used to mount the part to the printed circuit board.

(6) **Part marking:** There may be an additional marking, which relates to the logo, the lot trace code information, or the environmental category of the part.

Multiple part markings will be inside parentheses. Only one part marking contained in parentheses and separated by a "~" will appear on a part. If a line is indented then it is a continuation of the previous line and the two combined represent the entire part marking for that device.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

OTHER QUALIFIED VERSIONS OF ISO7041 :

- Automotive : ISO7041-Q1

NOTE: Qualified Version Definitions:

- Automotive - Q100 devices qualified for high-reliability automotive applications targeting zero defects

TAPE AND REEL INFORMATION

REEL DIMENSIONS



TAPE DIMENSIONS



A0	Dimension designed to accommodate the component width
B0	Dimension designed to accommodate the component length
K0	Dimension designed to accommodate the component thickness
W	Overall width of the carrier tape
P1	Pitch between successive cavity centers

QUADRANT ASSIGNMENTS FOR PIN 1 ORIENTATION IN TAPE



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Reel Diameter (mm)	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P1 (mm)	W (mm)	Pin1 Quadrant
ISO7041DBQR	SSOP	DBQ	16	2500	330.0	12.4	6.4	5.2	2.1	8.0	12.0	Q1
ISO7041FDBQR	SSOP	DBQ	16	2500	330.0	12.4	6.4	5.2	2.1	8.0	12.0	Q1

TAPE AND REEL BOX DIMENSIONS



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Length (mm)	Width (mm)	Height (mm)
ISO7041DBQR	SSOP	DBQ	16	2500	350.0	350.0	43.0
ISO7041FDBQR	SSOP	DBQ	16	2500	350.0	350.0	43.0

TUBE



*All dimensions are nominal

Device	Package Name	Package Type	Pins	SPQ	L (mm)	W (mm)	T (µm)	B (mm)
ISO7041DBQ	DBQ	SSOP	16	75	505.46	6.76	3810	4
ISO7041FDBQ	DBQ	SSOP	16	75	505.46	6.76	3810	4



PACKAGE OUTLINE

DBQ0016A

SSOP - 1.75 mm max height

SHRINK SMALL-OUTLINE PACKAGE



NOTES:

1. Linear dimensions are in inches [millimeters]. Dimensions in parenthesis are for reference only. Controlling dimensions are in inches. Dimensioning and tolerancing per ASME Y14.5M.
2. This drawing is subject to change without notice.
3. This dimension does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed .006 inch, per side.
4. This dimension does not include interlead flash.
5. Reference JEDEC registration MO-137, variation AB.



LAND PATTERN EXAMPLE
SCALE:8X



SOLDER MASK DETAILS

4214846/A 03/2014

NOTES: (continued)

6. Publication IPC-7351 may have alternate designs.
7. Solder mask tolerances between and around signal pads can vary based on board fabrication site.

EXAMPLE STENCIL DESIGN

DBQ0016A

SSOP - 1.75 mm max height

SHRINK SMALL-OUTLINE PACKAGE



SOLDER PASTE EXAMPLE
BASED ON .005 INCH [0.127 MM] THICK STENCIL
SCALE:8X

4214846/A 03/2014

NOTES: (continued)

8. Laser cutting apertures with trapezoidal walls and rounded corners may offer better paste release. IPC-7525 may have alternate design recommendations.
9. Board assembly site may have different recommendations for stencil design.

IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATASHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES “AS IS” AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, regulatory or other requirements.

These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you fully indemnify TI and its representatives against any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI’s products are provided subject to TI’s Terms of Sale, TI’s General Quality Guidelines, or other applicable terms available either on ti.com or provided in conjunction with such TI products. TI’s provision of these resources does not expand or otherwise alter TI’s applicable warranties or warranty disclaimers for TI products. Unless TI explicitly designates a product as custom or customer-specified, TI products are standard, catalog, general purpose devices.

TI objects to and rejects any additional or different terms you may propose.

Copyright © 2026, Texas Instruments Incorporated

Last updated 10/2025